

# CIO-DAS08

## Specifications



**MEASUREMENT  
COMPUTING™**

Document Revision 5.1, February, 2010  
© Copyright 2010, Measurement Computing Corporation

# Specifications

Typical for 25 °C unless otherwise specified.

Specifications in *italic text* are guaranteed by design.

## Analog input

Table 1. Analog input specifications

Parameter	Specification																
<i>A/D converter type</i>	<i>AD574</i>																
Resolution	12-bits																
Number of channels	8 single-ended																
Input ranges	$\pm 10$ V, $\pm 5$ V, 0 to +10 V, switch selectable																
Polarity	Unipolar/Bipolar, switch selectable																
A/D pacing	Software polled (typically through ISR paced by on-board counter)																
A/D trigger sources	External polled digital input trigger (Digital In 1)																
Data transfer	Software polled (typically through ISR paced by on-board counter)																
DMA	None																
<i>A/D conversion time</i>	<i>25 <math>\mu</math>s</i>																
Throughput	20 kHz, PC dependent																
Accuracy	$\pm 0.01\%$ of reading $\pm 1$ LSB																
Differential linearity error	$\pm 1$ LSB																
Integral linearity error	$\pm 0.5$ LSB																
<i>No missing codes guaranteed</i>	<i>12-bits</i>																
<i>Gain drift (A/D specs)</i>	<i><math>\pm 25</math> ppm/<math>^{\circ}</math>C</i>																
<i>Zero drift (A/D specs)</i>	<i><math>\pm 10</math> <math>\mu</math>V/<math>^{\circ}</math>C</i>																
Common Mode Range	$\pm 10$ V																
CMRR	72 dB																
<i>Input leakage current (@ 25 <math>^{\circ}</math>C)</i>	<i>100 nA</i>																
<i>Input impedance</i>	<i>10 Meg Ohms min</i>																
<i>Absolute maximum input voltage</i>	<i><math>\pm 35</math> V</i>																
Noise Distribution (Rate = 1 to 20 kHz)	<table border="1"> <thead> <tr> <th></th> <th>Avg % <math>\pm 2</math> bins</th> <th>Avg % <math>\pm 1</math> bin</th> <th>Avg # bins</th> </tr> </thead> <tbody> <tr> <td>Bipolar (10 V)</td> <td>100%</td> <td>100%</td> <td>3 bins</td> </tr> <tr> <td>Bipolar (5 V)</td> <td>100%</td> <td>100%</td> <td>3 bins</td> </tr> <tr> <td>Unipolar (10 V)</td> <td>100%</td> <td>100%</td> <td>3 bins</td> </tr> </tbody> </table>		Avg % $\pm 2$ bins	Avg % $\pm 1$ bin	Avg # bins	Bipolar (10 V)	100%	100%	3 bins	Bipolar (5 V)	100%	100%	3 bins	Unipolar (10 V)	100%	100%	3 bins
	Avg % $\pm 2$ bins	Avg % $\pm 1$ bin	Avg # bins														
Bipolar (10 V)	100%	100%	3 bins														
Bipolar (5 V)	100%	100%	3 bins														
Unipolar (10 V)	100%	100%	3 bins														

## Digital Input / Output

Table 2. Digital input/output specifications (main connector – J1)

<i>Digital type (main connector J1)</i>	<i>Output: 74LS273 Input: 74LS244</i>
<i>Configuration</i>	<i>4 fixed output bits, 3 fixed input bits</i>
<i>Number of channels</i>	<i>4 out, 3 in</i>
<i>Output high</i>	<i>2.7 volts min @ -0.4 mA</i>
<i>Output low</i>	<i>0.4 volts max @ 8 mA</i>
<i>Input high</i>	<i>2.0 volts min, 7 volts absolute max</i>
<i>Input low</i>	<i>0.8 volts max, -0.5 volts absolute min</i>
<i>Output power-up / reset state</i>	

Table 3. Digital input/output specifications (digital connector – J2)

<i>Digital type (digital I/O connector J2)</i>	<i>82C55</i>
<i>Configuration</i>	<i>2 banks of 8, 2 banks of 4, programmable by bank as input or output</i>
<i>Number of channels</i>	<i>24 I/O</i>
<i>Output high</i>	<i>3.0 volts min @ -2.5 mA</i>
<i>Output low</i>	<i>0.4 volts max @ 2.5 mA</i>
<i>Input high</i>	<i>2.0 volts min, 5.5 volts absolute max</i>
<i>Input low</i>	<i>0.8 volts max, -0.5 volts absolute min</i>
<i>Power-up / reset state</i>	<i>Input mode (high impedance)</i>

Table 4. Interrupt specifications

Interrupts	2 - 7, jumper selectable
Interrupt enable	Programmable
Interrupt sources	External (Interrupt In), rising edge; on-board counter, jumper selectable

## Counters

Table 5. Counter specifications

<i>Counter type</i>	<i>82C54</i>
<i>Configuration</i>	<i>3 down counters, 16-bits each</i>
Counter 0 — Independent, user configurable	Source: User connector (Counter 0 In) Gate: User connector (Gate 0) Output: User connector (Counter 0 Out)
Counter 1 — Independent, user configurable	Source: User connector (Counter 1 In) Gate: User connector (Gate 1) Output: User connector (Counter 1 Out)
Counter 2 — Independent, user configurable	Source: PC SysClk via divide by 2 circuit Gate: User connector (Gate 2) Output: User connector (Counter 2 Out)
<i>Clock input frequency</i>	<i>10 MHz max</i>
<i>High pulse width (clock input)</i>	<i>30 ns min</i>
<i>Low pulse width (clock input)</i>	<i>50 ns min</i>
<i>Gate width high</i>	<i>50 ns min</i>
<i>Gate width low</i>	<i>50 ns min</i>
<i>Input low voltage</i>	<i>0.8 V max</i>
<i>Input high voltage</i>	<i>2.0 V min</i>
<i>Output low voltage</i>	<i>0.4 V max</i>
<i>Output high voltage</i>	<i>3.0 V min</i>

## Power consumption

Table 6. Power consumption specifications

Parameter	Specification
+5V	250 mA typical, 312 mA max
+12V	15 mA typical, 21 mA max
-12V	25 mA typical, 35 mA max

## Environmental

Table 7. Environmental specifications

<i>Operating temperature range</i>	<i>0 to 50 ° C</i>
<i>Storage temperature range</i>	<i>-20 to 70 ° C</i>
<i>Humidity</i>	<i>0 to 90% non-condensing</i>

## Main connectors and pin out

Table 8. Connector specifications

Connector type	Analog connector (J1): 37-pin male "D" connector
	Digital connector (J2): 37-pin male "D" connector
Compatible cables with analog connector J1	C37FF-x C37-FFS-x
Compatible cables with digital connector J2	BP-37
Compatible accessory products with the C37FF-x cable, C37FFS-x cable, and the BP-37 cable	CIO-MINI37 CIO-TERMINAL CIO-SPADE50 CIO-EXP16 CIO-EXP32

### Analog connector J1 pin out

Table 9. Analog connector J1 pin out

Pin	Signal Name	Pin	Signal Name
1	+12V PC Bus	20	-12V PC Bus
2	Counter 0 In	21	Gate 0
3	Counter 0 Out	22	Gate 1
4	Counter 1 In	23	Gate 3
5	Counter 1 Out	24	Interrupt Input
6	Counter 2 Out	25	Digital In 1
7	Digital Out 1	26	Digital In 2
8	Digital Out 2	27	Digital In 3
9	Digital Out 3	28	Dig GND
10	Digital Out 4	29	+5V
11	Dig Common	30	CH7 High
12	LLGND	31	CH6 High
13	LLGND	32	CH5 High
14	LLGND	33	CH4 High
15	LLGND	34	CH3 High
16	LLGND	35	CH2 High
17	LLGND	36	CH1 High
18	LLGND	37	CH0 High
19	+10V Ref		

## Digital connector J2 pin out

Table 10. Digital connector J2 pin out

Pin	Signal Name	Pin	Signal Name
1	NC	20	+5V
2	NC	21	GND
3	FIRSPORTB Bit 7	22	FIRSPORTC Bit 7
4	FIRSPORTB Bit 6	23	FIRSPORTC Bit 6
5	FIRSPORTB Bit 5	24	FIRSPORTC Bit 5
6	FIRSPORTB Bit 4	25	FIRSPORTC Bit 4
7	FIRSPORTB Bit 3	26	FIRSPORTC Bit 3
8	FIRSPORTB Bit 2	27	FIRSPORTC Bit 2
9	FIRSPORTB Bit 1	28	FIRSPORTC Bit 1
10	FIRSPORTB Bit 0	29	FIRSPORTC Bit 0
11	GND	30	FIRSPORTA Bit 7
12	-5V	31	FIRSPORTA Bit 6
13	GND	32	FIRSPORTA Bit 5
14	-12V	33	FIRSPORTA Bit 4
15	GND	34	FIRSPORTA Bit 3
16	+12V	35	FIRSPORTA Bit 2
17	GND	36	FIRSPORTA Bit 1
18	+5V	37	FIRSPORTA Bit 0
19	GND		

**Measurement Computing Corporation**  
**10 Commerce Way**  
**Suite 1008**  
**Norton, Massachusetts 02766**  
**(508) 946-5100**  
**Fax: (508) 946-9500**  
**E-mail: [info@mccdag.com](mailto:info@mccdag.com)**  
**[www.mccdag.com](http://www.mccdag.com)**