

SPECIFICATIONS

CIO-EXP-BRIDGE16

Bridge Signal Conditioning



**MEASUREMENT
COMPUTING™**

Revision 2, January, 2001

© Copyright 2001, MEASUREMENT COMPUTING CORPORATION

Power Consumption

+5V (excluding any power to bridges) 250 mA typical, 350 mA maximum

Analog Input Section

Input amplifier type	INA102
Number of channels	16 differential
Gains	Each channel individually switch-selectable for X1, X10, X100 or custom, and board gain switch-selectable for X1 or X2.5
Gain Error	
Gain = 1, 2.5	0.01% typical, 0.15% maximum
Gain = 10, 25	0.02% typical, 0.35% maximum
Gain = 100, 250	0.05% typical, 0.40% maximum
Gain = 1000, 2500	0.20% typical, 0.90% maximum
Linearity	
Gain = 1, 2.5	0.045% typical
Gain = 10, 25	0.045% typical
Gain = 100, 250	0.075% typical
Gain = 1000, 2500	0.15% typical
Input Offset	Each channel adjustable to zero
Gain TC	
Gain = 1	10 ppm/°C typical
Gain = 100	15 ppm/°C typical
Gain = 1000	20 ppm/°C typical
Input Offset TC	
Gain = 1, 2.5	20 μ V/°C typical
Gain = 10, 25	6 μ V/°C typical
Gain = 100, 250	5.1 μ V/°C typical
Gain = 1000, 2500	5.1 μ V/°C typical
Common Mode Range	± 10 V
CMRR	
Gain = 10, 25, 100, 250, 1000, 2500	100 dB typical
Gain = 1, 2.5	94 dB typical
Channel to channel settling time	
5V step to .01%	250 μ s
Absolute maximum input voltage	± 15 V
Miscellaneous	Each input channel has a 79 Hz low pass filter. X2.5 gain is adjustable for zero error. Jumper selects compatibility with DAS08 or DAS16 series Locations provided for bridge completion resistors for each channel. Locations provided for bridge nulling pots and resistors for each channel.

Analog Output

Output Amplifier type	OP07
Number of channels	1
Maximum Output Range	± 10 V
Current Drive	± 5 mA
Output short-circuit duration	25 mA indefinite

Output coupling	DC
Output impedance	100 Ohms maximum
Miscellaneous	Output jumper selectable for one of 16 channels (P1 & P2 Output - to Output 15)

Digital Input / Output

Digital type	HI508A multiplexer
DIn 0 through 2	2N2222 transistor inverter
DIn 3	
Configuration	4 digital inputs for selecting multiplexer channel
Input low voltage	
DIn 0 through 2	0.8V max, -4V absolute minimum
DIn 3	1.0V max, -4V absolute minimum
Input high voltage	
DIn 0 through 2	2.4V min, 9V absolute maximum
DIn 3	1.27V min, 9V absolute maximum

Voltage Excitation Section

Excitation voltages	10V, 4V, 2V, 1V, 0.5V
Sources for excitation voltage	5V from PC, 5V from MOLEX, 12V from PC, external (\pm PEXT screw terminal)
Current	
5V source, 4V VEXC	333 mA
12V source, 10V VEXC	833 mA
15V external source, 10 VEXC	1.333 A
Miscellaneous	Output jumper-selectable for one of 16 channels (P1 & P2 Output - to Output 15) Voltage adjustable for zero error

Environmental

Operating temperature range	0 to 60°C
Storage temperature range	-40 to 100°C
Humidity	0 to 90% non-condensing

Measurement Computing Corporation
10 Commerce Way
Suite 1008
Norton, Massachusetts 02766
(508) 946-5100
Fax: (508) 946-9500
E-mail: info@mccdaq.com
www.mccdaq.com